

## SUMMARY TABLE OF CONTROLS N-COM B902L R SERIES

		<i>Button</i>	n	on	▲	▼	▲ + ▼
<b>Basic Functions</b>	Turning on			2 sec			
	Turning off			6 sec			
	Increase Volume				X		
	Decrease Volume					X	
	Management of Lights Menu						2 sec
	Pairing up Menu***			4 sec			
	Configuration Menu						4 sec
<b>Bluetooth Devices</b>	Answer phone call*	X	X	X	X		
	Voice call			2 sec			
	Speed Dialling Menu**	X	X				
	Hang up/reject a phone call			2 sec			
	Manual Device Connection			2 sec			
	Phone Conference Activation CHANNEL 1	X					
	Phone Conference Activation CHANNEL 2	x2					
	Phone Conference Activation CHANNEL 3	x3					
	Turning off the Conference function	X					
<b>Bluetooth Music / Cable</b>	Play music (Play)			X			
	Pause Function (Pause)			X			
	Next track (Forward)				2 sec		
	Previous track (REW)					2 sec	
	Share A2DP music			X			
	Activate audio via cable			x3			
	Deactivate audio via cable			x3			
<b>N-Com Intercom (900 series)</b>	Connection CHANNEL 1	X					
	Disconnection of active intercom	X					
	Calling CHANNEL 2	x2					
	Calling CHANNEL 3	x3					
	Group intercom connection	2 sec					
	Group intercom disconnection	X					
<b>Radio Menu</b>	Turning on the Radio			x2			
	Turning off the Radio			x2			
	Automatic search for new station				2 sec		
	Change station (pre-set stations)					2 sec	
	Pre-set station					4 sec	

\*Press any key on the N-Com keypad.

\*\*Press the keys at the same time.

\*\*\*Starting with the system switched off.